

Local: 480.946.0267 Toll Free: 888.660.5029 Fax: 480.946.1471 Web: usaradiorentals.com

SPRINT PTT Instructions

To Turn on: Press the Red (END) Power button on keypad. **To Turn off:** Hold the Red (END) Power button on keypad.

Using the Radio:



- Press the *Contacts key (right top button on keypad),* then simply scroll up or down using the **navigation keys** to select the <u>desired name</u>.

- Push and Hold the *PTT Button* on the side of the radio and listen for "Connection Tone Sound" before speaking. *Note: This is the go-ahead and speak signal, wait for it, or you will cut off the start of your conversation.*

- Then Release the *PTT Button* to listen for a response.

NOTE: For *Group Call*, Select the **group name** from your contacts list. All radios programmed for Group Call will be able to talk & listen at the same time.

Using Headphones / Speaker Mics / Surveillance Kits – Earpieces

<u>Shut off radio</u>, then insert plug straight and firmly into the *Audio Jack*, turn the radio back on. **Note:** if you experience a problem accessory or keyed up radio, shut it off disconnect and repeat this procedure.

Charging the Radio

Attach/insert **MICRO USB** charger intoto the left side of phone (open little latch). The LCD screen will show charging taking place. A full charge will show a full-battery in the LCD screen.

Note: At least 2-Radios must be **Turned On** and on the <u>same channel</u> to be able to talk. If there are no other units on your channel or within range, then the radio will Bonk when you try to talk. This is a good thing, because if your call goes through, you know that someone is on your channel with their unit powered on within range of you, and they received your call.